

Figure 1: Uploading FIRMWARE.DLF.

Firmware update procedure

- 1. Connect to ADSLRouter via Ethernet cable and log-in Router.
- 2. Click the "Reset to Factory Default" on admin privilege and reboot.
- 3. Enable the FTP Server on Misc configuration and save.
- 4. Click Code image update in admin privilege
 - (a) Click Browse button in right page
 - (b) Choose FIRMWARE.DLF then click upload button. The message "you must reboot the system now" will appear.
 - (c) Click the reboot button now!!



Figure 2: Uploading bootrom.dlf.

- 5. After the router rebooted successfully:
 - (a) Click code image update in admin privilege.
 - (b) Click Browse button in right page.
 - (c) Choose bootrom.dlf then click upload button. The system will be rebooted.

🗿 Conexant - Hasbani - Microsoft Internet Explorer 📃 🖻 🔀				
File Edit View Favorites Tools	Help			
🕞 Back 🔹 💿 🕤 📓 🚮 🔎 Search 🤶 Favorites 🜒 Media 🤣 😒 - چ 🚍				
Address 🕘 http://10.0.0.2/				💙 🔁 Go 🛛 Links 🎽
ADSL Configuration	Home Page			
<u>RIP Configuration</u>	Firmware Version: ETHADSL_USB_080902_REL9K-A2 Customer Software Version: CA8XR-HL-082103.00F			
Password Configuration Admin				
User				
Misc Configuration	WAIN			
Reset to Factory Default	IP Address	Subnet Mask	MAC Address	
Diagnostic Test	0.0.0.0	255.0.0.0	00:D0:41:00:00:05	
Code Image Update				
Network Code Image	LAN			
System Log	IP Address	Subnet Mask	MAC Address	~
Done Internet				
🛃 start 🛛 😂 📴 📼 Comr	mand Pro 🦉 05 - Paint	🙆 Conexant - Ha	🗢 Local Disk (C:)	🔇 🛤 🔷 12:12 PM

Figure 3: The end result should look like this.